



LED Crystal Ball User's Manual

Model:L001

Attention

1. Please read these operating instructions carefully to familiarize you with basic operations of this unit BEFORE USE.
2. Without permitted, it is prohibited to spread the contents of this manual to others.
3. This manual is only to provide related information, and the contents of this manual will be changed at any time without notice.
4. Unless the instructions have already stated, please do not freely modified the unit.

Safety Tips

1. Before installation and maintenance, please confirm the power is OFF. make sure that the ventilation around the unit is good.
2. The lighting is designed for indoor demonstration, please do not use this product in a wet environment for long-term.
3. The use and maintenance of this unit should avoid contact with water. when using it outdoor, please take waterproofing measures.
4. Personnel, who to take the installation, operation and maintenance, must be familiar with the lighting performance. Most of the damage is resulted from unfamiliar with its performance.
5. Please do not face up to the luminous unit for a long time, so as not to cause discomfort to your eyes.
6. Please often wipe the unit with a clean cloth.

Operating Instructions

Menu	NO.	Descriptions
A1	1-9	Red&Blue, motor speed from slow to fast
A2		Pink&Green, motor speed from slow to fast
A3		Yellow&White, motor speed from slow to fast
A4		2 colors transition, motor speed from slow to fast
A5		2.4.6 colors transition, motor speed from slow to fast
A6		Gradual Change1, motor speed from slow to fast
A7		Gradual Change2, motor speed from slow to fast
S1	0-20	Colors strobe by sound control, no sound no light, motor working
S2		Colors transition by sound control, motor working
A	001-512	DMX or Slave mode

Address code A001-slave function

Technical Parameters

Light source	6x3W RGBOWP LED
Source lifetime	Rated 50,000 hours
Power supply	100-240V/50-60HZ
Rating power	30W
Play mode	Auto/Sound/DMX/Master-slave
DMX channel	6
Effect	Crystal magic ball/Disco ball with 6 rings, strong plastic case with 82 strong beams light, water running effects with strobe, speed & brightness adjustable, color can be changed with the program selected
Dimensions	183×183×154mm
Gross weight	0.75KG

DMX Control

Channels	Numerical	Functions Descriptions
CH 1	0-9	Light on(This channel should use together with Ch2,Ch3,Ch4)
	10-255	Strobe speed from slow to fast
CH 2	0	Red&Blue light off
	1-255	Light brightness from dark to bright
CH 3	0	Pink&Green light off
	1-255	Light brightness from dark to bright
CH 4	0	Yellow&White light off
	1-255	Light brightness from dark to bright
CH 5	0-9	Motor shut down
	10-127	Motor place control
	128-255	Motor clockwise or counter-clockwise rotation, speed from slow to fast
CH 6	0-9	Manual mode
	10-205	Built-in program
	206-233	Colors strobe by sound control, no sound no light, motor working
	234-255	Colors transition by sound control, motor working

Note: "MENU" is the Function Transforming Button, "UP & DOWN" is the Number Transforming Button, "ENTER" is the Confirm Button.

Big Dipper Laser Science And Technology Co., Ltd

All products made from Big Dipper Laser Company have anti - fake identification. please verify the anti-counterfeit label at the bottom of the case to ensure the interests of consumers.